

```

ENTITY mx2_x2 IS
  GENERIC (
    CONSTANT area          : NATURAL := 2250;
    CONSTANT cin_cmd       : NATURAL := 17;
    CONSTANT cin_i0        : NATURAL := 8;
    CONSTANT cin_il        : NATURAL := 9;
    CONSTANT rdown_cmd_q   : NATURAL := 1620;
    CONSTANT rdown_i0_q    : NATURAL := 1620;
    CONSTANT rdown_il_q    : NATURAL := 1620;
    CONSTANT rup_cmd_q     : NATURAL := 1790;
    CONSTANT rup_i0_q      : NATURAL := 1790;
    CONSTANT rup_il_q      : NATURAL := 1790;
    CONSTANT tphh_i0_q     : NATURAL := 451;
    CONSTANT tphh_il_q     : NATURAL := 451;
    CONSTANT tp11_i0_q     : NATURAL := 469;
    CONSTANT tp11_il_q     : NATURAL := 469;
    CONSTANT tphh_cmd_q    : NATURAL := 484;
    CONSTANT tphl_cmd_q    : NATURAL := 485;
    CONSTANT tp11_cmd_q    : NATURAL := 522;
    CONSTANT tp1h_cmd_q    : NATURAL := 534;
    CONSTANT transistors   : NATURAL := 12
  );
  PORT (
    cmd      : IN  BIT;
    i0       : IN  BIT;
    i1       : IN  BIT;
    q        : OUT BIT;
    vdd      : IN  BIT;
    vss      : IN  BIT
  );
END mx2_x2;

ARCHITECTURE vbe OF mx2_x2 IS

BEGIN
  ASSERT ((vdd and not (vss)) = '1')
  REPORT "power supply is missing on mx2_x2"
  SEVERITY WARNING;
  q <= ((i1 AND cmd) OR (NOT (cmd) AND i0)) AFTER 1100 ps;
END;

```