

```

ENTITY xr2_x1 IS
  GENERIC (
    CONSTANT area          : NATURAL := 2250;
    CONSTANT cin_i0        : NATURAL := 21;
    CONSTANT cin_i1        : NATURAL := 22;
    CONSTANT rdown_i0_q    : NATURAL := 2850;
    CONSTANT rdown_i1_q    : NATURAL := 2850;
    CONSTANT rup_i0_q      : NATURAL := 3210;
    CONSTANT rup_i1_q      : NATURAL := 3210;
    CONSTANT tplh_i1_q     : NATURAL := 261;
    CONSTANT tphl_i0_q     : NATURAL := 292;
    CONSTANT tplh_i0_q     : NATURAL := 293;
    CONSTANT tphh_i0_q     : NATURAL := 366;
    CONSTANT tphl_i1_q     : NATURAL := 377;
    CONSTANT tp1l_i1_q     : NATURAL := 388;
    CONSTANT tp1l_i0_q     : NATURAL := 389;
    CONSTANT tphh_i1_q     : NATURAL := 405;
    CONSTANT transistors   : NATURAL := 12
  );
  PORT (
    i0      : IN  BIT;
    i1      : IN  BIT;
    q       : OUT BIT;
    vdd     : IN  BIT;
    vss     : IN  BIT
  );
END xr2_x1;

ARCHITECTURE vbe OF xr2_x1 IS

BEGIN
  ASSERT ((vdd AND NOT (vss)) = '1')
  REPORT "power supply is missing on xr2_x1"
  SEVERITY WARNING;
  q <= (i0 XOR i1) AFTER 1000 ps;
END;

```